


ARTNET controller Setting Manual

www.colordreamer.com

1. Connection with PC

Step 1

Connect the controller with PC by RJ 45 ethernet cable. Power on the controller



Step 2

Set your computer's IP to let the computer and controller to be in the **same network**

Artnet controller default IP is


192.168.1.100

User need to set your computer IP to be

192.168.1.XXX

(XXX is number from 1 to 255, but except 100)


Subnet Mask:255.255.255.0



Step3

Open your web browser and enter the IP address 192.168.1.100
Web configuration interface will be launched.

That means the artnet controller was connected with your PC.




Colordreamer Titan Configuration - Windows Internet Explorer

http://192.168.1.100/

收藏夹 | 建议网站 | 网页快讯库

Colordreamer Titan Configuration



Titan

Device Information	
Model	Colordreamer Titan A8 PRO2
Firmware	1.001
Hardware	1.001
IP Address	192.168.001.100
MAC Address	84:B3:BB:D4:12:01


[Device Configuration](#)

For more information visit www.colordreamer.com

2. Connect with Madrix


Step1

You can download demo version of Madrix from www.madrix.com. Start the software,click perferences-Device Manager, there will show a window as below



Step 2


Click Art-Net tab, check in the Art-Net option, and select the network card which is connecting with controller. Then select Pre Sync or Post Sync in Sync area, finally,click the Find Auto to search Art-Net device. Here shows the search result window. (We are using 16 port artnet controller, so there are 16 universe.



Step 3

Click the DMX Devices tab, select the port of controller, check in Enable in the right, then click the Apply to confirm all the setting.

Please make sure the status of your universe is “on”.



※ There is one Artnet Remote (Madrix) Port 0 in the below, please don't enable that


3. Change Controller's IP address

Step1

Open your web browser and enter the IP address 192.168.1.100

Web configuration interface will be launched.

Click “**Device Configuration**”




Colordreamer Titan Configuration - Windows Internet Explorer

http://192.168.1.100/

收藏夹 | 建议网站 | 网页快讯库

Colordreamer Titan Configuration



Titan

Device Information	
Model	Colordreamer Titan A8 PRO2
Firmware	1.001
Hardware	1.001
IP Address	192.168.001.100
MAC Address	84:B3:BB:D4:12:01

Device Configuration

For more information visit www.colordreamer.com

Step 2:

User can change IP address and save this configuration

“Change” IP Address

Click “Save”

Titan

Device Settings		
General Network Settings		
IP Address	192 . 168 . 1 . 100	
Subnet Mask	255 . 255 . 255 . 0	
Network Input Settings		
Network Protocol	Art_Net Protocol	
Net	Sub Net	Send Always Full Frames (512 Ch.)
0	0	<input type="checkbox"/>
Configuration Reset		Save
		Return
		Exit

For more information visit <http://www.colordreamer.com/>

Step3:

After saving all setting, reboot the system to apply the new setting

Reboot

After reboot, this window will be closely automatically

Titan

Your settings have been saved, reboot the system to apply the new settings.

Reboot

For more information visit www.colordreamer.com